

Summit Technology's FX3000 Flexible Current Probe offers 10 to 3000 Amp AC current measurements.

Specifications

- 10 to 3000 A_{RMS} AC Current measurement

Accuracy

- 2% of reading +/- 0.2 amps (for currents below 400 A_{RMS}) or +/- 2 Arms (for currents from 400-3000 A_{RMS})

Dimensions

- 24.0 inch Flexible Circumference
- Inside diameter of 7.5 inches
- Outside measurement of 24.0 x .85 inches



Power Requirements

The probe connects directly into PowerSight®. No additional batteries are required.

Pricing and Availability

The FX3000 is available for immediate purchase from Summit Technology Inc. and is priced at \$395.00 each. To order, specify **FX3000**.

PowerSight® Energy Analyzer is manufactured in the USA and sold by Summit Technology, Inc.

For more information on our products contact:

Summit Technology Inc.
2717 N. Main St., Suite 15
Walnut Creek, CA 94597-2747

Voice: 1-925-944-1212
Fax: 1-925-944-7126
Email: sales@SummitTechnology.com

PowerSight® is a trademark of Summit Technology. Prices and specifications are subject to change without notice.